


REC2 Series


條型光源




REC2 背部散熱板

◆ 產品特色


- 高密度LED陣列提供高亮度與高均勻度
- 採用特殊光學鏡片可改變LED放射角度
- 採用標準模具確保組裝穩定與品質
- 可客製發光面長度與光源波長、色溫
- 可選配擴散片與透鏡角度
- 加強散熱設計，增加使用壽命




▼ Illuminated angle diagram



有含擴散片



20度



40度

◆ 產品型號

REC2 - 74 X 30 - R - WD

Series REC = Bar Light	Emitting Length 74 = 74mm	Emitting Width 30 = 30mm	Color R = Red	Illuminated Angle WD = 40 degree
---------------------------	------------------------------	-----------------------------	------------------	-------------------------------------

REC2 - 386 X 30 - D - B - WD

Series REC = Bar Light	Emitting Length 386 = 386mm	Emitting Width 30 = 30mm	D = Diffuser	Color B = Blue	Illuminated Angle WD = 40 degree
---------------------------	--------------------------------	-----------------------------	--------------	-------------------	-------------------------------------

◆ 系列規格表

Model	Voltage	Color	Power (W)		Dimensions (mm)			Diagrams
			●	●●○	Length	Width	Height	
REC2-41X16	24V	●●●○	1	1.5	53	20	19	1
REC2-80X16	24V	●●●○	2	2.5	92	20	19	2
REC2-119X16	24V	●●●○	3	4	131	20	19	3
REC2-158X16	24V	●●●○	4	6	170	20	19	4
REC2-197X16	24V	●●●○	5	6.5	209	20	19	5
REC2-74X30	24V	●●●○	3.5	5	86	34	19	6
REC2-98X30	24V	●●●○	4.8	6	110	34	19	7
REC2-146X30	24V	●●●○	7.2	10	158	34	19	8
REC2-170X30	24V	●●●○	8.4	11	182	34	19	9
REC2-194X30	24V	●●●○	9.5	12	206	34	19	10
REC2-218X30	24V	●●●○	10.7	15	230	34	19	11
REC2-266X30	24V	●●●○	13	17	278	34	19	12
REC2-290X30	24V	●●●○	14.2	18	302	34	19	13
REC2-386X30	24V	●●●○	19.2	24	398	34	19	14
REC2-434X30	24V	●●●○	21.5	30	446	34	19	15
REC2-578X30	24V	●●●○	28.8	36	590	34	19	16

(mm)

◆ 產品尺寸圖

<p>1</p> <p>Hex Nut M3 Groove For Installation</p> <p>2-M3 x 3 Same In The Opposite For Installation</p> <p>REC2-41X16</p>	<p>2</p> <p>Hex Nut M3 Groove For Installation</p> <p>2-M3 x 3 Same In The Opposite For Installation</p> <p>REC2-80X16</p>
<p>3</p> <p>Hex Nut M3 Groove For Installation</p> <p>2-M3 x 3 Same In The Opposite For Installation</p> <p>REC2-119X16</p>	<p>4</p> <p>Hex Nut M3 Groove For Installation</p> <p>2-M3 x 3 Same In The Opposite For Installation</p> <p>REC2-158X16</p>
<p>5</p> <p>Hex Nut M3 Groove For Installation</p> <p>2-M3 x 3 Same In The Opposite For Installation</p> <p>REC2-197X16</p>	<p>6</p> <p>Hex Nut M3 Groove (For Installation)</p> <p>4-M3 depth 4</p> <p>REC2-74X30</p>
<p>7</p> <p>Hex Nut M3 Groove (For Installation)</p> <p>4-M3 depth 4 (For Installation)</p> <p>REC2-98X30</p>	<p>8</p> <p>Hex Nut M3 Groove (For Installation)</p> <p>4-M3 depth 4 (For Installation)</p> <p>REC2-146X30</p>
<p>9</p> <p>Hex Nut M3 Groove (For Installation)</p> <p>4-M3 depth 4 (For Installation)</p> <p>REC2-170X30</p>	<p>10</p> <p>Hex Nut M3 Groove (For Installation)</p> <p>4-M3 depth 4 (For Installation)</p> <p>REC2-194X30</p>
<p>11</p> <p>Hex Nut M3 Groove (For Installation)</p> <p>4-M3 depth 4 (For Installation)</p> <p>REC2-218X30</p>	<p>12</p> <p>Hex Nut M3 Groove (For Installation)</p> <p>4-M3 depth 4 (For Installation)</p> <p>REC2-266X30</p>
<p>13</p> <p>Hex Nut M3 Groove (For Installation)</p> <p>4-M3 depth 4 (For Installation)</p> <p>REC2-290X30</p>	<p>14</p> <p>Hex Nut M3 Groove (For Installation)</p> <p>4-M3 depth 4 (For Installation)</p> <p>REC2-386X30</p>
<p>15</p> <p>Hex Nut M3 Groove (For Installation)</p> <p>4-M3 depth 4 (For Installation)</p> <p>REC2-434X30</p>	<p>16</p> <p>Hex Nut M3 Groove (For Installation)</p> <p>4-M3 depth 4 (For Installation)</p> <p>REC2-578X30</p>